

## IPC/PTZ/NVR upgrade on web 5

Tiandy Technical Support Team 23/08/2020

### Description

IPC/PTZ/NVR upgrade on web5

### Prerequisites

- Already got FW

### Set up steps

1. Choose English here then enter the user name/password and login.



The screenshot shows the Tiandy web interface. At the top left is the Tiandy logo. At the top right is a language selection dropdown menu with 'English' selected and highlighted by a red box. Below the logo, there are three input fields: 'User Name' with 'admin' entered, 'Password' (empty), and 'Port' with '3000' entered. A green 'Login' button is positioned below the input fields.

2. Select 'Configuration'.

The screenshot shows the Tiandy web interface with the 'Configuration' menu highlighted in red. The 'Stream Set' configuration page is displayed, featuring a sidebar with navigation options and a main content area with various settings. The 'General Set' section includes dropdown menus for Resolution (1080P(1920x1080)), Frame Rate (25), N/P Mode (PAL), Priority (Frame Rate), and Video Quality (Good). There are also input fields for Bit Rate (4096) and I-Frame Interval (50), and a dropdown for Encoding Mode (Variable Bit Rate). A 'Smooth Video Streaming' slider is set to 50, with a label '[Clarity<->Smooth]'.

3. Choose 'Advance Set'-'System Maintenance'.

The screenshot shows the Tiandy web interface with the 'System Maintenance' option in the sidebar highlighted in red. The 'System Maintenance' page is displayed, featuring a sidebar with navigation options and a main content area with various system control options. The 'Device Control' section includes buttons for 'Basic Recovery', 'Comple..ecovery', 'Reboot', and 'Open re..service'. The 'Configuration In/Out' section includes an 'Import' field with a file type filter (\*.box) and 'Browse' and 'Import' buttons, and an 'Export' button. The 'Firmware Upgrade' section includes an 'Upgrade File' field with a file type filter (\*.bin)or(\*.box) and 'Browse' and 'Upgrade' buttons.

4. Find 'Firmware Upgrade' and click 'Browse' to choose the upgrade box we send you.

The screenshot shows the Tiandy web interface with the 'Configuration' tab selected. The left sidebar contains a menu with 'System Maintenance' highlighted. The main content area is titled 'System Maintenance' and includes sections for 'Device Control' (with buttons for Basic Recovery, Complet...covery, Reboot, and Open re...service), 'Configuration In/Out' (with an Import field for \*.box files and an Export button), and 'Firmware Upgrade' (with an Upgrade File field for \*.bin or \*.box files and a highlighted Browse button). The 'Firmware Upgrade' link and the 'Browse' button are both highlighted with red boxes.

5. Click 'Upgrade' to finish S3E/S6 upgrade on web5. Do not turn off the power during upgrading.